

Accelerator Physics Particle Acceleration

G. A. Krafft Old Dominion University Jefferson Lab Lecture 7







Graduate Accelerator Physics Fall 2015

Convert Fundamental Solutions

• Convert usual phase space variables

$$x_{1}(z) = \sqrt{\beta_{x_{I}}} \cos \phi_{x_{I}} \quad x_{1}'(z) = \sqrt{\gamma_{x_{I}}} \cos \psi_{x_{I}}$$
$$\rightarrow \gamma_{x_{I}} = \frac{\beta_{x_{I}}^{2} \phi_{x_{I}}'^{2} + \alpha_{x_{I}}^{2}}{\beta_{x_{I}}} \quad \psi_{x_{I}} = \phi_{x_{I}} - \tan^{-1} \frac{\beta_{x_{I}} \phi_{x_{I}}'}{\alpha_{x_{I}}}$$

• Points of hyper-ellipsoid

$$v(z) = \begin{pmatrix} x \\ x' \\ y \\ y' \end{pmatrix} = \sqrt{\varepsilon_{I}} \begin{pmatrix} \sqrt{\beta_{x_{I}}(z)} \cos(\phi_{x_{I}} + \theta_{I}) \\ \sqrt{\gamma_{x_{I}}(z)} \cos(\psi_{x_{I}} + \theta_{I}) \\ \sqrt{\beta_{y_{I}}(z)} \cos(\phi_{y_{I}} + \theta_{I}) \\ \sqrt{\gamma_{y_{I}}(z)} \cos(\psi_{y_{I}} + \theta_{I}) \end{pmatrix} \cos \chi + \sqrt{\varepsilon_{II}} \begin{pmatrix} \sqrt{\beta_{x_{II}}(z)} \cos(\phi_{x_{II}} + \theta_{II}) \\ \sqrt{\gamma_{x_{II}}(z)} \cos(\psi_{x_{II}} + \theta_{II}) \\ \sqrt{\beta_{y_{II}}(z)} \cos(\psi_{y_{I}} + \theta_{I}) \end{pmatrix} \sin \chi$$





Beam size





Thomas Jefferson National Accelerator Facility



Graduate Accelerator Physics Fall 2015

Beam Tilt



• Project *x*-*y* plane

$$E_{(x,y)} = \sqrt{\varepsilon_I \beta_{(x,y)_I} + \varepsilon_{II} \beta_{(x,y)_{II}}}$$
$$E_{xy} = \frac{\varepsilon_I \sqrt{\beta_{x_I} \beta_{y_I}} \cos \Delta \phi_I + \varepsilon_{II} \sqrt{\beta_{x_{II}} \beta_{y_{II}}} \cos \Delta \phi_{II}}{E_x}$$

$$\Delta \phi_{I,II} = \phi_{x_{I,II}} - \phi_{y_{I,II}}$$

$$\tan 2\psi = \frac{2E_x E_y}{E_x^2 - E_y^2} = 2\frac{\varepsilon_I \sqrt{\beta_{x_I} \beta_{y_I}} \cos \Delta \phi_I + \varepsilon_{II} \sqrt{\beta_{x_{II}} \beta_{y_{II}}} \cos \Delta \phi_{II}}{\varepsilon_I \Delta \beta_I + \varepsilon_{II} \Delta \beta_{II}}$$



Thomas Jefferson National Accelerator Facility



Graduate Accelerator Physics Fall 2015

Beam sizes





Ellipse equation

$$\frac{x^{2}}{a_{x}^{2}} - \frac{2\tilde{\alpha}xy}{a_{x}a_{y}} + \frac{y^{2}}{a_{y}^{2}} = 1 - \tilde{\alpha}^{2}$$



Ellipse rotation parameter

$$\widetilde{\alpha} = \frac{\langle xy \rangle}{\sqrt{\langle x^2 \rangle \langle y^2 \rangle}} = \frac{\widetilde{y}}{a_y} = \frac{\widetilde{x}}{a_x} = \frac{\sqrt{\beta_{1x}\beta_{1y}}\varepsilon_1 \cos v_1 + \sqrt{\beta_{2x}\beta_{2y}}\varepsilon_2 \cos v_2}}{\sqrt{\varepsilon_1\beta_{1x}} + \varepsilon_2\beta_{2x}} \sqrt{\varepsilon_1\beta_{1y}} + \varepsilon_2\beta_{2y}}$$



Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 7 – Coupled Betatron Motion I

USPAS, Fort Collins, CO, June 10-21, 2013 5



and



Jefferson Lab

Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 - Coupled Betatron Motion II



 At the exit of the solenoid the electron beam distribution is still axially symmetric

$$\boldsymbol{\Xi}_{in} = \boldsymbol{\Phi}^{T} \boldsymbol{\Xi}_{B} \boldsymbol{\Phi} = \frac{1}{\varepsilon_{T}} \begin{bmatrix} \gamma_{0} + \Phi^{2} \beta_{0} & \alpha_{0} & 0 & -\Phi \beta_{0} \\ \alpha_{0} & \beta_{0} & \Phi \beta_{0} & 0 \\ 0 & \Phi \beta_{0} & \gamma_{0} + \Phi^{2} \beta_{0} & \alpha_{0} \\ -\Phi \beta_{0} & 0 & \alpha_{0} & \beta_{0} \end{bmatrix}$$

where

$$\mathbf{\Phi} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & \Phi & 0 \\ 0 & 0 & 1 & 0 \\ -\Phi & 0 & 0 & 1 \end{bmatrix}$$

• $\Phi = eB/2P_0c$ is the rotational focusing strength of the solenoid

▲ B is the solenoid magnetic field.

Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Jefferson Lab

Lecture 9 – Coupled Betatron Motion II



• The eigen-vectors of the rotational distribution:

$$\hat{\mathbf{v}}_{1} = \begin{bmatrix} \sqrt{\beta} \\ -\frac{i+2\alpha}{2\sqrt{\beta}} \\ i\sqrt{\beta} \\ -i\frac{i+2\alpha}{2\sqrt{\beta}} \end{bmatrix} , \qquad \hat{\mathbf{v}}_{2} = \begin{bmatrix} i\sqrt{\beta} \\ -i\frac{i+2\alpha}{2\sqrt{\beta}} \\ \sqrt{\beta} \\ -\frac{i+2\alpha}{2\sqrt{\beta}} \end{bmatrix}$$

• It corresponds to u = 1/2, $v_1 = v_2 = \pi/2$

• Then, the matrix $\hat{\mathbf{V}}$ is

$$\hat{\mathbf{V}} = \begin{bmatrix} \sqrt{\beta} & 0 & 0 & -\sqrt{\beta} \\ -\frac{\alpha}{\sqrt{\beta}} & \frac{1}{2\sqrt{\beta}} & \frac{1}{2\sqrt{\beta}} & \frac{\alpha}{\sqrt{\beta}} \\ 0 & -\sqrt{\beta} & \sqrt{\beta} & 0 \\ \frac{1}{2\sqrt{\beta}} & \frac{\alpha}{\sqrt{\beta}} & -\frac{\alpha}{\sqrt{\beta}} & \frac{1}{2\sqrt{\beta}} \end{bmatrix}$$



Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 8



Comparing left and right hand sides of the equation

$$\hat{\boldsymbol{\Xi}}_{in} = \mathbf{U}\hat{\mathbf{V}} \begin{bmatrix} 1/\varepsilon_1 & 0 & 0 & 0\\ 0 & 1/\varepsilon_1 & 0 & 0\\ 0 & 0 & 1/\varepsilon_2 & 0\\ 0 & 0 & 0 & 1/\varepsilon_2 \end{bmatrix} \hat{\mathbf{V}}^T \mathbf{U}^T$$

One obtains



4D-emmitance conservation:

$$\varepsilon_1 \varepsilon_2 = \varepsilon_T^2$$

Rotational emittance estimate

$$\varepsilon_{rot} = r\theta = r(r\Phi) = r^2\Phi = (\varepsilon_T\beta_0)\Phi$$

Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 - Coupled Betatron Motion II

Spin Rotators for Figure-8 Collider Ring







Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 10

Spin Rotator – Ingredients...



Jefferson Lab

Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II USPAS, Fort Collins, CO, June 10-21, 2013

11

Locally Decoupled Solenoid Pair





Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

Locally Decoupled Solenoid Pair





Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 13

Universal Spin Rotator - Optics



Jefferson Lab

Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

Ionization Cooling in an Axially Symmetric Channel



A single-particle phase-space trajectory along the beam orbit can be expressed as:

$$\hat{\mathbf{x}}(s) = \operatorname{Re}\left(\sqrt{\varepsilon_{1}}\hat{\mathbf{v}}_{1}(s)e^{-i(\psi_{1}+\mu_{1}(s))} + \sqrt{\varepsilon_{2}}\hat{\mathbf{v}}_{2}(s)e^{-i(\psi_{2}+\mu_{2}(s))}\right) ,$$

One can rewrite the above equations in the following compact form

 $\hat{\mathbf{x}}(s) = \hat{\mathbf{V}}(s)\mathbf{a}(s)$

where

$$\hat{\mathbf{V}}(s) = \begin{bmatrix} \mathbf{v}_1'(s), -\hat{\mathbf{v}}_1''(s), \hat{\mathbf{v}}_2'(s), -\hat{\mathbf{v}}_2''(s) \end{bmatrix} \quad \mathbf{a}(s) = \begin{bmatrix} \sqrt{\varepsilon_1} \cos(\psi_1 + \mu_1(s)) \\ \sqrt{\varepsilon_1} \sin(\psi_1 + \mu_1(s)) \\ \sqrt{\varepsilon_2} \cos(\psi_2 + \mu_2(s)) \\ \sqrt{\varepsilon_2} \sin(\psi_2 + \mu_2(s)) \end{bmatrix}$$



Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

Vertex-to-plane Transformer Insert







Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 16



 Eigen-vectors of the decoupled motion in the coordinate system rotated by 45°



A Rotational eigen-vectors

 $\begin{bmatrix} \mathbf{F}_2 \\ i\mathbf{F}_2 \end{bmatrix} \begin{bmatrix} i\mathbf{F}_2 \\ \mathbf{F}_2 \end{bmatrix}$



Thomas Jefferson National Accelerator Facility

Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 17



- Focusing system with 45[°] difference between the horizontal and vertical betatron phase advances will transform the initial vertex distribution into the flat one
- The resulting 2D emittances are as follows

$$\varepsilon_1 = \frac{\varepsilon_T}{\sqrt{1 + \Phi^2 \beta_0^2} - \Phi \beta_0} \quad , \qquad \varepsilon_2 = \frac{\varepsilon_T}{\sqrt{1 + \Phi^2 \beta_0^2} + \Phi \beta_0}$$

Lattice implementation – Twiss functions, beam sizes etc.



Thomas Jefferson National Accelerator Facility

Vertex-to-plane Transformer Insert





Operated by JSA for the U.S. Department of Energy

Lecture 9 – Coupled Betatron Motion II

USPAS, Fort Collins, CO, June 10-21, 2013 19





Northern Illinois Center for Accelerator and Detector Development



Philippe Piot,

Department of Physics and Northern Illinois Center for Accelerator & Detector Development, Northern Illinois University, DeKalb IL 60115

Accelerator Physics Center, Fermi National Accelerator Laboratory, Batavia IL 60510

Yin-e Sun,

Advanced Photon Source, Argonne National Laboratory, Argonne IL 60439

International Workshop on Accelerator Science & Technologies for future electron-ion colliders (EIC'14), Jefferson Lab, March 17-21, 2014

*sponsored by the DOE awards DE-FG02-08ER41532 to Northern Illinois University and DE-AC02-07CH11359 to the Fermi Research Alliance LLC.

Outline

- Introduction
- Features and parameterization of magnetized beams
- Formation of magnetized bunches:
 - methods and limitations,
 - experiments in rf gun.
- Transport and Manipulation:
 - transverse matching,
 - longitudinal manipulations,
 - decoupling into flat beams.
- Outlook

Required Electron-Beam Parameters

- Cooling interaction
 time
 - $au pprox
 ho/v_{e\perp}$ (not magnetized) $au pprox rac{
 ho}{v pprox v_{e\parallel}}$ (magnetized)
- magnetized cooling less dependent on e- beam transverse emittance (to what extent?)



 electron-cooling accelerator provides beam eventually matched to coolingsolenoid section

Cooler configurations

low-energy coolers:

S. Nagaitsev, et al, PRL96, 044801 (2006)

e.g. see

- lattice (bends) embedded in magnetic fields,
- based on DC electron sources,
- no further acceleration or bunching, needed.



- medium energies
 required (50-100
 MeV),
- acceleration in SCRF linac \rightarrow bunching
- − lumped solenoidal fields → matching



P. Piot, EIC'14, JLab, Mar. 17-21, 2014

High-energy coolers



- injector: produces bunched beam for RF acceleration
- debuncher: matched electron bunch length to ion-beam's,
- matching + mode/converter sections: repartition "physical" emittances, match in cooling-solenoid section.



Beam dynamics regimes (round beams)

• Radial envelope (σ) equation in a drift (Lawson):



. Chicago (2005)

adapted from Y.-E Sun, Dissertation U

Features & Parameterization

- possible parameterization of coupled motion between 2 degrees of freedom has been extensively discussed; see:
 - D.A. Edwards and L.C. Teng, IEEE Trans. Nucl. Sci. 20, 3, pp. 885-889 (1973).
 - I. Borchardt, E. Karantzoulis, H. Mais, G. Ripken, DESY 87-161 (1987).
 - V. Lebedev, S. A. Bogacz, ArXiV:1207.5526 (2007).
 - A. Burov, S. Nagaitsev, A. Shemyakin, Ya. Derbenev, PRSTAB 3, 094002 (2000).
 - A. Burov, S. Nagaitsev, Ya. Derbenev, PRE 66, 016503 (2002).
- Simpler description that provides the necessary insights..

A simple description of coupled motion

Consider the 4x4 beam matrix

$$\Sigma \equiv \begin{bmatrix} \langle \mathbf{X} \widetilde{\mathbf{X}} \rangle & \langle \mathbf{X} \widetilde{\mathbf{Y}} \rangle \\ \langle \mathbf{Y} \widetilde{\mathbf{X}} \rangle & \langle \mathbf{Y} \widetilde{\mathbf{Y}} \rangle \end{bmatrix} \quad \text{where} \quad \begin{array}{l} \widetilde{\mathbf{X}} \equiv (x, x') \\ \widetilde{\mathbf{Y}} \equiv (y, y') \end{array}$$

- Introduce the "correlation" matrix: $C \equiv \langle \mathbf{Y} \widetilde{\mathbf{X}} \rangle \langle \mathbf{X} \widetilde{\mathbf{X}} \rangle^{-1}$
- Beam matrix takes the form:

$$\Sigma = \left(\begin{bmatrix} I & 0 \\ 0 & I \end{bmatrix} + \begin{bmatrix} 0 & C^{-1} \\ C & 0 \end{bmatrix} \right) \begin{bmatrix} \langle \mathbf{X} \widetilde{\mathbf{X}} \rangle & 0 \\ 0 & \langle \mathbf{Y} \widetilde{\mathbf{Y}} \rangle \end{bmatrix}$$

• The correlation subjects to $R = \begin{bmatrix} H & G \\ U & V \end{bmatrix}$ transforms as $C_0 \to C$

$$C = (U + VC_0)(H + GC_0)^{-1}$$

• *C* provides information on the coupling only. P. Piot, EIC'14, JLab, Mar. 17-21, 2014

Beam matrix for a round magnetized beam

 At a waist, the matrix of a magnetized (round) beam is

$$\Sigma_0 = \begin{bmatrix} \varepsilon T_0 & \mathcal{L}J \\ -\mathcal{L}J & \varepsilon T_0 \end{bmatrix}.$$

where
$$T_0 = \begin{bmatrix} \beta & -\alpha \\ -\alpha & \frac{1+\alpha^2}{\beta} \end{bmatrix}$$

and the magnetization is

$$\mathcal{L} = \langle xy' \rangle = -\langle x'y \rangle = \frac{L}{2p_z}$$

• The eigen-emittances of this beam matrix are:

 $\varepsilon_{\pm} = \varepsilon \pm \mathcal{L}.$ where $\varepsilon^2 = \mathcal{L}^2 + \varepsilon_u^2 = |\Sigma|$

• the eigen-emittances can be mapped into "physical" emittances using a skewed beamline $\begin{bmatrix} M_+ & M_- \\ M_- & M_+ \end{bmatrix}$ decoupling when $\begin{bmatrix} M_- + M_+ C_0 = 0. \end{bmatrix}$

K.-J. Kim, PRSTAB 6, 104002 (2003) D. A. Edwards, unpublished (2001)

Formation of magnetized bunches

- Cathode immersed
 in an axial **B** field
- Sheet beams at birth (with subsequent flat-to-round beam converter)
 - shaped cathode,
 - line-laser focus
 - Nonlinear optics
 - (speculative)





Y. Derbenev, University of Michigan report UM-HE-98-04 (1998)

G. Florentini, et al., Proc. PAC95, p. 973 (1996)

P. Piot, ŒIC'14, JLab, Mar. 17-21, 2014

Cathode in a magnetic field

• electrons born in an axial B field $B_z \rightarrow CAM$

$$L(r) = erA_{\theta} \simeq \frac{er^2}{2}B_{z,0} + \mathcal{O}(r^4)$$

• upon exit of solenoid field ($A_{\theta} = 0$): CAM becomes purely kinetic.



Emittance vs magnetization

• "effective emittance" $\varepsilon^2 = \mathcal{L}^2 + \varepsilon_u^2$



• Practically, ε_u includes other contributions.

P. Piot, EIC'14, JLab, Mar. 17-21, 2014

Example of 3.2-nC magnetized bunch

- high-charge bunch subject to emittance degradation
- proper optimization

 (emittance compensation)
 → 4-D emittance comparable to round beams.





Measuring (kinetic) angular momentum

• Kinetic angular momentum can be measured using a slit technique (similar to emittance)



• The beam's average angular momentum is given by $\sigma_{1,}$

$$\langle L \rangle = 2P_z \frac{\sigma_1 \sigma_2 \sin \theta}{D}$$

 $\sigma_{1,2}$: rms beam size at slit (1) and observation screen (2), P_z : axial momentum D: drift length between locations (1) and (2).

P. Piot, EIC'14, JLab, Mar. 17-21, 2014

Experimental generation in a photoinjector

- Fermilab A0 normal-conducting photoinjector (decommissioned),
- 15 MeV, charge up to 2 nC,~3-10 ps bunch



Experimental generation in a photoinjector

linear scaling with B field on photocathode



P. Piot, EIC'14, JLab, Mar. 17-21, 2014

Experimental generation in a photoinjector

<L> (neV s)

120

100

80

60

40

20

 $B_{z} = 962 \text{ G}$

 $\sigma_{c} = 0.82 \pm 0.05 \text{ mm}$

- weak Q dependence,
- quadratic scaling with laser spot size σ_c on photocathode.



Decoupling into flat ($\epsilon_x/\epsilon_y \neq 1$ **) beam**

- Transport of magnetized bunches while preserving ${\cal L}$ is challenging,
- Use of round-to-flat beam transformer to convert into uncoupled (flat) beam
 → eigen-emittances maps into "physical" transverse emittances:

$$\begin{split} \varepsilon_n^{\pm} &= \sqrt{(\varepsilon_n^u)^2 + (\beta \gamma \mathcal{L})^2} \\ &\pm (\beta \gamma \mathcal{L})^{\beta \gamma \mathcal{L} \gg \varepsilon_n^u} \begin{cases} \varepsilon_n^+ &\simeq 2\beta \gamma \mathcal{L}, \\ \varepsilon_n^- &\simeq \frac{(\varepsilon_n^u)^2}{2\beta \gamma \mathcal{L}}, \end{cases} \end{split}$$

Decoupling into flat beam: experiments (1)

 Same experimental setup as used for generation of CAM-dominated beams



Decoupling into flat beam: experiments (2)

- normal emittances map into the flatbeam emittance
- large experimental uncertainties for smallest emittance meas.

Parameter	Experiment	Simulation	Unit
σ_x^{X7}	$0.088 \pm 0.01 \ (\pm 0.01)$	0.058	mm
σ_{v}^{X7}	$0.63 \pm 0.01 \ (\pm 0.01)$	0.77	mm
$\sigma_x^{X8,v}$	$0.12 \pm 0.01 \ (\pm 0.01)$	0.11	mm
$\sigma_y^{X8,h}$	$1.68 \pm 0.09 \ (\pm 0.01)$	1.50	mm
$\boldsymbol{\varepsilon}_n^x$	$0.41 \pm 0.06 \ (\pm 0.02)$	0.27	μ m
$\boldsymbol{\varepsilon}_n^{\boldsymbol{y}}$	$41.1 \pm 2.5 \ (\pm 0.54)$	53	μ m
$\varepsilon_n^y/\varepsilon_n^x$	$100.2 \pm 20.2 \ (\pm 5.2)$	196	

80 70 10¹ X7 X8 60 Х3 σ 50



P. Piot, EIC'14, JLab, Mar. 17-21, 2014

Outlook + open questions

- magnetized beam from a SCRF gun:
 - flux concentrator around cathode?
 - flat beam at cathode
 - [J. Rosenzweig, PAC93 showed ($\varepsilon_+\varepsilon_-$)=(95,4.5) µm]
- needed ϵ_u and \mathcal{L} ? and limit on 4-D emittance?
- planned future experiment at ASTA

